



CASAMBI  
READY

CE

Technische Daten <i>Technical data</i>	schwarz <i>black</i>	weiß <i>white</i>
Artikelnummer <i>Part no.</i>	<b>800671</b>	<b>800672</b>
Typ <i>Type</i>	RWBTB	RWBTW
Funksignal <i>Radio signal</i>	2,4..2,483 GHz; 4 dBm	
Funksignalreichweite <i>Radio signal range</i>	bis zu 60 Meter <i>up to 60 meters</i>	
Batterie <i>Battery</i>	CR 2430 Lithium-ion	
Batterie Lebensdauer <i>Battery lifetime</i>	2 - 5 Jahre <i>years</i>	
Abmessungen <i>Dimensions</i>	90 x 90 x 12 mm	

- Fernbedienung zur Steuerung von Geräten in CASAMBI-Netzwerken
- 4 Tasten (heller / dunkler, warm- / kaltweiß)
- 4 frei programmierbare Tasten (Szenen, Farbe,...)
- Programmierung erfolgt per Smartphone / Tablet (Apple, Android) mit der CASAMBI-App
- Die Lebensdauer der Batterie hängt vom Gebrauch ab
- Die Fernbedienung selbst ist magnetisch. Im Lieferumfang enthalten ist eine Grundplatte zur freien Montage, mit Metallplatten zur magnetischen Aufnahme.

- Remote control for controlling devices inside CASAMBI networks
- 4 buttons (brighter / darker, warm / cool white)
- 4 free programmable buttons (scenes, colour,...)
- Programming via smartphone / tablet (Apple, Android) with the CASAMBI app
- The battery lifetime depends on the usage
- The remote control itself is magnetic. The delivery includes a base plate for free assembly, with metal plates for magnetic mounting.

